# TECH LIGHTING

### **PRODUCT FEATURES**

- · Modern Style
- · Lighting designed to project modern simplicity
- · Illuminates a smooth wash of light through an LED diffuser
- Protected by a 5-year warranty. Please visit the "About Us" Page on techlighting.com for more for warranty details



### LAMPING

Includes 21.2 watts, 869 total delivered lumens, 3000K LED modules. Dimmable with most LED compatible ELV and TRIAC dimmers. Ships with 12 feet of field-cuttable black cloth cord. 120V-277V





#### ORDERING INFORMATION

700TDKOSA LENGTH (A)	FINISH	LAMP
<b>18</b> 18"	<b>W</b> MATTE WHITE	-LED930 INTEGRATED LED 90 CRI 3000K 120V-277V UNV
	B NIGHTSHADE BLACK	

700TDKOSA	
JOB NAME	
NOTES	




# **KOSA 18 PENDANT**

# TECH LIGHTING

### **SPECIFICATIONS**

HARDWARE MATERIAL	Metal
SHADE MATERIAL	Acrylic
NET WEIGHT	
HEIGHT	4.4in
WIDTH	18in
LENGTH	18in
UP LIGHT / DOWN LIGHT / BOTH?	
WET LISTED	
DAMP LISTED	Yes
DRY LISTED	
MIN. HANGING HEIGHT	7.8in
MAX HANGING HEIGHT	148.9in
TOTAL CORD LENGTH	144in
TOTAL STEM LENGTH	
STEM QTY	
SLOPED CEILING ADAPTABLE?	Yes 45° Max
GENERAL LISTING	ETL Listed
INCLUDES	



### LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS		869		
WATTS		21.2		
MAX WATTAGE PER BULB		21.2W		
INPUT VOLTAGE		Universal 120V-277VV		
DIMMING TYPE*		ELV, TRIAC		
ССТ		3000K		
CRI		90 CRI		
LED LIFETIME				
L70		>50000		
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE		Integrated LED		
LAMP SHAPE		Integrated LED		
LAMP INCLUDED?		Υ		
WARRANTY**		5 Years		

 $<sup>* \ \, \</sup>text{Dimming information available at} \, \underline{\text{www.techlighting.com/Downloads\#dimming}}$ 

# T20 / T24 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6.	Yes		
This product can be used to comply with California Appliance Efficiency Standards 2016 <b>Title 20</b> and may be shipped to and sold in California.	N/A		

 $<sup>^*</sup>$  If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.



<sup>\*\*</sup> Visit techlighting.com for specific warranty limitations and details.